

# HEX BAND INSULATORS



## DIMENSIONAL DATA

| ITEM NAME                             | ITEM CODE | D1 | D2 | H   | A/F | F  | INSERT |    | INSERT |    | Rated Voltage | Test Voltage<br>(For 1 Min) |
|---------------------------------------|-----------|----|----|-----|-----|----|--------|----|--------|----|---------------|-----------------------------|
|                                       |           |    |    |     |     |    | T1     | L1 | T2     | L2 |               |                             |
| HEXAGONAL BAND INSULATOR M6 X 25 HT   | HEX0625   | 16 | 19 | 25  | 23  | 11 | M6     | 9  | M6     | 9  | 440 V         | 2 KV                        |
| HEXAGONAL BAND INSULATOR M10 X 50 HT  | HEX1050   | 38 | 44 | 50  | 48  | 20 | M10    | 20 | M10    | 20 | 440 V         | 2 KV                        |
| HEXAGONAL BAND INSULATOR M12 X 60 HT  | HEX1260   | 37 | 40 | 60  | 50  | 20 | M12    | 25 | M12    | 25 | 600 V         | 2 KV                        |
| HEXAGONAL BAND INSULATOR M12 X 75 HT  | HEX1275   | 39 | 43 | 75  | 49  | 25 | M12    | 25 | M12    | 25 | 600 V         | 2 KV                        |
| HEXAGONAL BAND INSULATOR M12 X 100 HT | HEX12100  | 37 | 45 | 100 | 60  | 28 | M12    | 25 | M12    | 25 | 600 V         | 2 KV                        |
| HEXAGONAL BAND INSULATOR M8 X 30 HT   | HEX0830   | 25 | 27 | 30  | 31  | 15 | M8     | 13 | M8     | 13 | 440 V         | 2 KV                        |
| HEXAGONAL BAND INSULATOR M8 X 35 HT   | HEX0835   | 25 | 28 | 35  | 32  | 15 | M8     | 13 | M8     | 13 | 440 V         | 2 KV                        |

\* Insert sizes could also be varied to suit customer requirement